

JTElectronics Beacon Flasher

Model: JTEBF1



The JTEBF1 Beacon Flasher will flash 6 volt lamps (or LEDs with appropriate series current limiting resistor) at an adjustable "OFF" rate between about 10 to 120 seconds. The lamp "ON" time can also be adjusted between about 0.5 and 3 seconds. It can be powered from 7 to 24 volts DC, or 5 to 16 volts AC. It will power lamp(s) at 6 volts and up to 500 milliamps. It is important not to "short out" the lamp connections as this will damage the output circuitry.

